

Arcam A25+

Geïntegreerde versterkers



Technische specificaties

Merk	Arcam
Model	A25+
Productcategorie	Geïntegreerde versterkers
Analoge ingangen	Aantal ingangen 3 (RCA pairs); Signaal-ruisverhouding (A-wtd, ref. 50W, 1V input) 106dB; Frequentierespons 20Hz-20kHz $\pm$ 0.2dB
Digitale ingangen	Ondersteund Sample Rates (kHz); USB-C Only 384, 352.8, 192, 176.4, 96, 88.2, 48, 44.1; Other digital inputs 192, 176.4, 96, 88.2, 48, 44.1; Bitdieptes (bit) 32, 24, 16; Frequentierespons (filter 1) 20Hz-20kHz $\pm$ 0.2dB; Signaal-ruisverhouding (A-wtd, ref. 50W, 0dBFS) 109dB
Continu uitgangsvermogen (0.5% THD), per channel	2 kanalen aangestuurd, 20Hz - 20kHz, 8 Ω 100W; 2 kanalen aangestuurd, 1kHz, 4 Ω 165W; Harmonische vervorming, 80% power, 8 Ω at 1kHz 0.002%
Hoofdtelefoonuitgang	Maximaal uitgangsniveau (RMS) into 32 Ω /300 Ω 2.5V/5V; Belastingsbereik 16 Ω - 2k Ω

Technische specificaties

Draadloze verbindingen	Bluetooth Version - 5.4; A2DP Sink/Source, AVRCP, BLE, SBC, AAC, aptX, aptX HD and aptX Lossless, LE Audio, Auracast; Bluetooth Transmitter Frequency and Power - 2,400 MHz to 2,483.5 MHz: <20dBm
Algemeen	Mains voltage 100V or 110-120V or 220-240V, 50-60Hz; Power consumption (maximum) 500W; Power consumption (standby) <0.5W; Dimensions W x D (including speaker terminals) x H (including feet) 431 x 344 x 83mm; Weight (net) 9kg; Weight (packed) 12kg
Meegeleverde accessoires	Mains lead(s); Remote control with 2 x AAA batteries; Quick Start Guide; Important Safety Instructions
Netspanning	100V or 110-120V or 220-240V, 50-60Hz
Maximaal stroomverbruik	500W
Stroomverbruik in stand-by	<0.5W
Afmetingen (B x D x H), mm	431 x 344 x 83mm
Verzendgewicht	12kg
Nettogewicht	9kg