

Arcam SA35

Geïntegreerde versterkers



Technische specificaties

Merk	Arcam
Model	SA35
Productcategorie	Geïntegreerde versterkers
Analoge ingangen	Aantal ingangen: 3 (RCA pairs); Phono-ingangs: MM and MC; Frequentierespons: 20Hz-20kHz $\pm$ 0.2dB; Signaal-ruisverhouding (A-wtd, ref. 50W, 1V input): 106dB
Continu uitgangsvermogen (0.5% THD), per channel	2 kanalen aangestuurd, 20Hz - 20kHz, 8 Ω : 120W; 2 kanalen aangestuurd, 1kHz, 4 Ω : 200W; Harmonische vervorming, 80% power, 8 Ω at 1kHz: 0.002%
Algemeen	Mains voltage: 100V or 110-120V or 220-240V, 50-60Hz; Power consumption (maximum): 700W; Power consumption (standby): <0.5W; Dimensions W x D (including speaker terminals) x H (including feet); 432 x 344 x 99mm; Weight (net): 12 kg; Weight (packed): 14 kg
Meegeleverde accessoires	Mains lead(s); Remote control with 2 x AAA batteries; Measurement Microphone; 5m USB Cable; Quick Start Guide; Important Safety Instructions

Technische specificaties

Netspanning	100V or 110-120V or 220-240V, 50-60Hz
Maximaal stroomverbruik	700W
Stroomverbruik in stand-by	<0.5W
Verzendgewicht	14 kg
Nettogewicht	12 kg