

Cambridge Audio Edge A

Geïntegreerde versterkers



Technische specificaties

Merk	Cambridge Audio
Model	Edge A
Productcategorie	Geïntegreerde versterkers
Continu uitgangsvermogen	100W RMS into 8 Ω ; 200W RMS into 4 Ω
Frequentiebereik	<3Hz - >80kHz +/-1dB
Ingangen	Balanced, Coax S/PDIF, TOSLINK, USB Audio, Unbalanced, Bluetooth, Audio Return Channel (ARC)
Uitgangen	Speakers, Preamplifier, Headphones (impedance of between 12 and 600 Ω are recommended)
THD (unweighted)	<0.002% 1kHz at rated power (8 Ω); <0.02% 20Hz - 20kHz at rated power (8 Ω)
Signaal-ruisverhouding (ref full power)	>103 dB
Overspraak @ 1kHz	< -100dB

Technische specificaties

Ingangsgevoeligheid	Input A1-A2 (ongebalanceerd) 380mV RMS
Ingangsimpedanties	Input A3 (gebalanceerd) 47k Ohm; Input A1-A2 (ongebalanceerd) 47k Ohm
USB-audio-ingang	USB Audio Class 2.0 supporting tot 24-bit 384kHz PCM, or tot DSD256
Bluetooth	4.1 (Smart/BLE enabled) A2DP/AVRCP supporting formats tot aptX HD
Optische TOSLINK-ingang	16/24 bits, 32-96kHz
Coaxiale S/PDIF-ingang	16/24 bits, 32-192kHz
Maximaal stroomverbruik	1000W
Stroomverbruik in stand-by	<0.5W
Afmetingen	150 x 460 x 405mm (5.9 x 18.1 x 15.9")
Gewicht	24.4kg (53.7lbs)