

MartinLogan MDA16

Eindversterkers



Technische specificaties

Merk	MartinLogan
Model	MDA16
Productcategorie	Eindversterkers
Frequentiebereik	10Hz - 20kHz $\pm$ 0.5dB
Ingangen (analog)	8x RCA pairs (left/right)
Ingangen (digital S/PDIF)	2x RCA coaxial; 2x optical (Toslink)
Ingangen (network)	RJ-45 10Base-T/100 Base-TX ethernet port
Ingangen (trigger)	1x 3.5mm (5 - 24V DC/AC)
Uitgangen (speaker level)	8x removable Phoenix style (left/right) accommodate wire tot 12AWG
Uitgang (analog, passthrough)	2x RCA pair (left/right)
Uitgangen (subwoofer)	8x RCA (with bass management and room correction)
Uitgangen (digital matrix)	1x optical (Toslink)

Technische specificaties

Uitgangen (other)	1x 3.5mm 12V trigger
Afmetingen (H x W x D, with feet)	3.5" x 17" x 16.4" (8.9 x 43.2 x 41.7 cm)
Ruimtecorrectie	Anthem Room Correction (ARC®)
Ingangen (Other)	Micro-USB (for ARC); RS-232
Gewicht	24 lbs. (10.8kg)